

Specification Data Sheet


Rev 1.0 February 2014

Armour Home Electronics R&D Department




Systemline E100 is an integrated fitted music system which includes an OLED display and touch sensitive button keypad fitted in the wall. The keypad contains amplification for speakers, DAB/FM tuner, Bluetooth audio receiver and auxiliary line input all contained within one 45mm double gang wall socket. E100 also includes a clock and alarm and optional remote control. E100 has been designed to be very easy to install and very user friendly, making it perfect for kitchens, bedrooms and hotel rooms.

Wiring diagram




Specifications	
Radio	DAB/DAB+ and FM with RDS 4 preset stations
Bluetooth	Class 2 Bluetooth 2.1 apt-X for CD-quality transmission Secure pairing Passcode Selectable device name to allow multiple units to be used in close proximity Range up to 10m
Aux input	725mV Normal Gain or 250mV Boost Gain
Alarms	2 separate alarms configurable for daily, weekday or weekend operation
Languages supported	English, Chinese, Danish, Finnish, French, German, Italian, Norwegian, Spanish and Swedish
Power output	2 x 18W into 8 Ohms @ 0.5% THD 1kHz
Frequency response	20Hz – 20kHz +/- 1dB
Power supply	110-240 VAC

Accessories



Remote control



*All measurements in mm

armourHOME

Stortford Hall Industrial Park,
Dunmow Road, Bishops Stortford
Hertfordshire, CM23 5GZ, UK

t: +44 (0)1279 501111
f: +44 (0)1279 501080
info@armourhe.co.uk

www.systemline.co.uk

Q14807-AR_r0